

## EX2000 Quick Setup

After turning on the EX2000 the display will scroll:

<b>Default Screen:</b>	<b>Please Use Exact Change</b>
<b>Editable Screen 1:</b>	<b>B&amp;W \$0.10</b>
<b>Editable Screen 2:</b>	<b>Color \$0.20</b>
<b>Editable Screen 3:</b>	<b>Legal +\$0.10</b>
<b>Editable Screen 4:</b>	<b>Ledger +\$0.20</b>

**Note: View Service Manual to Edit Screen(s).**

### 1. Set Price

1. Turn operator key to the on position
2. Enter default service pin number found in Service Manual
3. **Supervisor Copy Mode** press **FWD**
4. **Enter Service Mode** press **ENTER**
5. **Meters Menu** press **FWD**
6. **Price Menu** press **ENTER**
7. **Edit Prices Cash Customers** press **ENTER**
8. **Cash Customers** (Price 1 \$0.10) press **ENTER**
9. Enter price per copy and press **ENTER**
10. Press **FORWARD** to edit price line(s) 2-4 and follow previous step (i)
11. Press **EXIT** to back out one level
12. **Edit Price Cash Customers** press **EXIT**
13. **Price Menu** press **EJECT** to exit the Service Mode

### 2. Load coin tubes

1. Turn operator key to the ON position
2. Enter default service pin number found in Service Manual
3. **Supervisor Copy Mode** press **ENTER**
4. Supervisor Count: **0**
5. Insert coins; NO CHANGE IN SCREEN but coins will be in memory
6. Press **EJECT** to exit. Display will now read **Insert Coin or Bill**